# STR922A-HDM

This is a high performance HDMI Matrix with two HDMI inputs & two outputs, it allows any source (Blue-Ray player, HD DVD player, satellite receiver, game system, etc.) to be shown on the any of the two displays simultaneously, and supports 4K×2K, 3D, 12-bit Deep Color. With its 3Gbps bandwidth and the additional features of the latest HDMI standards you can be sure of great HDMI distribution.

### Features:

- > Support display resolutions up to 4K x 2K@30Hz,1080P@120Hz, and 1080P 3D@60Hz
- >3D HDMI 1.4a video format support.
- >3D video support including Frame packing for all 3D formats up to a 297MHz TMDS clock.
- >Supports deep color up to 48-bit per pixel.
- >HDCP 1.4 support (INPUT), HDCP v1.4a protocol compliant (OUTPUT).
- >Supports the reception of any audio data conforming to the HDMI specification 1.4 such ad L-PCM at up to 192kHz, compressed audio (IEC 61937), DSD, DST, DTS and HBR
- >Full colorimetry including sYCC601, Adobe RGB, Adobe YCC601, xvYCC extended gamut color
- >Operates for TMDS clock frequencies up to 300MHz
- >Supports EDID control via EDID Selector.

# **Specifications:**

1pc HDMI Switch+1pc 5V1A DC Power Supply adaptor+1pc Remote Controller

Frequency Bandwidth: 2.97Gbps

Input Ports: 2 x HDMI Female input ports

Output Ports: 2 x HDMI Female output ports

Power Supply: DC 5V 1A

**ESD Protection Human Body Model:** ± 8kV (air-gap discharge)

± 4kV (contact discharge)

Dimensions (mm): 70(W) X 145 (D) X 25 (H)

Weight(g): 300

Operating Temperature:  $0^{\circ}$ C  $\sim 40^{\circ}$ C  $/ 32^{\circ}$ F  $\sim 104^{\circ}$ F


Storage Temperature: -20°C  $^{\sim}$  60°C / -4°F  $^{\sim}$  140°F

Relative Humidity: 20 ~ 90% RH (Non-condensing)

Power Consumption (Max): 5W

### **Operation controls and Functions:**

### **Rear Panel**




- ①**HDMI OUTPUT:** These slots are where you connect the HDTV or monitor With HDMI cable.
- ②HDMI INPUT: These slots are where you connect the HDMI source output From DVD, PS13.
- ③**DC IN:** Plug the 5V DC power supply into the unit and connect the adaptor to AC wall outlet.

# With EDID Control HDMI Matrix 2 x 2

# **Operation controls and Functions:**

### **Front Panel**



- (1)**ON/OFF:** Power on/off switch.
- ②**POWER LED:** This red LED illuminate when the device is connected with power supply.
- ③IR IN: Remote control signal receive.
- **4 OUTPUT A:** Press this button to select input sources to HDMI OUT A, and the LED will indicate the corresponding input source.
- ⑤OUTPUT B: Press this button to select input sources to HDMI OUT B, and the LED will indicate the corresponding input source.
- **©EDID Selector:** Select HDMI output signal format via EDID Selector.

Number	EDID Selector	Description
1	0000	1080P,Stereo Audio 2.0
2	0001	1080P,Dolby/DTS 5.1
3	0010	1080P,HD Audio 7.1
4	0011	1080I,Stereo Audio 2.0
5	0100	1080I,Dolby/DTS 5.1
6	0101	1080I,HD Audio 7.1
7	0110	3D,Stereo Audio 2.0
8	0111	3D,Dolby/DTS 5.1
9	1000	3D,HD Audio 7.1
10	1001	4K2K,Stereo Audio 2.0
11	1010	4K2K,Dolby/DTS 5.1
12	1011	4K2K,HD Audio 7.1
13	1100	Reserve
14	1101	Reserve
15	1110	Reserve
16	1111	Auto mode (default)

## **Application Example:**

